

# ACT-IR2012UL

## IrReady™ VFIR – USB ADAPTER

- Supports Win 98SE, Me, 2000, **Win XP, Windows Vista/7/8/8.1&10, Windows server 2003 (32 & 64 bit)**, with WHQL certified, Win CE 4.2 & 5.0 (USB host), Linux and Mac 10.x (both Intel & Power PC based).
- Simply attaches to USB port and gives user the wireless data transfer for data logging, synchronization, file transfer, backup, printing or network access.
- Supports VFIR (16Mbps), FIR (4Mbps), MIR (1.152M) and all SIR speeds ( 9.6k, 19.2k, 38.4k, 57.6k and 115.2k bps.)
- Compatible with any IrDA®-capable notebook PC, PDA, modem, printer, instrument, data terminal, digital camera, image capture device and others.
- Takes advantage of the true plug-and-play feature and the high bandwidth ( 12 Mbps ) of USB specification.
- Does not occupy PC's COM or Parallel port and has no complicated port and resource setting and conflict, such as I/O address, IRQ / DMA numbers.
- True PNP ( Plug And Play ) device and hot insertion capability !
- Fully compliant to USB specification 3.0 and IrDA specification 1.4
- Obtains power from USB port. No external power supply required. Low standby power (Less than 0.5 mA). Very compact size.



### ACT-IR2012UL

The only IrDA® adapter supplier that has test tools to help your system to be IrDA® compliant !



**ACTiSYS**  
The Infra-Red Wireless Expert



# SPECIFICATIONS

## *ACT-IR2012UL* *IrReady™ VFIR-USB Adapter*

- **Compatibility**

Fully compliant to USB specification 3.0 and IrDA® specification 1.4

- **Communication speed and Distance:**

9.6K, 19.2K, 38.4K, 57.6K, 115.2K bps: 1 cm-158 cm

1.152M, 4M, 16M bps: 1 cm-100 cm

- **Power Source:**

Obtain power from USB port. No external power supply required.

- **Power Consumption:**

Active current: < 400 mA, standby current: < 0.5 mA

- **Dimension / Weight:**

62 mm(L) X 36 mm(W) X 19 mm(H); Cable length=120 cm

61 g

- **Operating / Storage Temperature & Humidity:**

( 0 to +60 ) °C / ( -20 to +85 ) ° C ; 20% ~ 95%

- **Required Voltage:**

5V± 5%

 **ACTiSYS Corporation**

921 Corporate Way  
Fremont, CA 94539, U.S.A.  
Tel: +1-510-490-8024  
Fax: +1-510-623-7268  
email: [irda-info@actisys.com](mailto:irda-info@actisys.com)  
Web Site: <http://www.actisys.com>